

HIGHLIGHTS

- ✓ Wireless
- Coaxial and Optical inputs
- ✓ Sub output
- ✓ Headphone output 6.35mm
- CD/USB/AM/FM

LOGISTICAL DATA

EAN Code

Black: 0634654606167

DEEE

4.4 = 0,84 € H.T. = 1 € T.T.C.

Dimensions (WxHxD) & weight PRODUCT

280 x 99 x 310 mm / 5 Kg

PACKAGING

475 x 200 x 375 mm / 6.6 Kg

EM-702 Stereo system 2x35W - Wireless

? WIRELESS





The EM-702 was designed in an audiophile approach to ensure the high fidelity amater a faithful reproduction of his favourite music in a compact format. It delivers a power of 2x25W RMS into 8 Ω and 2x35W into 4 Ω .

It includes a CD player (MP3/WMA) as well as FM RDS and AM tuner with 40 station presets. Its USB slot allows you to play your digital files on USB key in MP3 and WMA formats.

The EM702 includes a WIRELESS receiver allowing you to listen to music from your smatphones and talbets. It has one anolog audio input (RCA Stereo), 1 digital input (Optical and / or Coaxial conections) allowing it to connect to TVs last generation.

Finally, it provides a Subwoofer output to connect an active subwoofer.

Digital Inputs: The OPTICAL connector will overide the source connected to COAXIAL, unless the source connected to the optical connector is turned off. In this case, you can listen to the source connected in coaxial.

MAIN FEATURES

- High quality manufacturing
- Shielded preamplifier
- 150VA Toroidal transformer
- WIRELESS connection with detachable antenna
- Optical and Coaxial digital inputs
- Subwoofer output
- USB input for MP3/WMA files formats
- AUX input in RCA
- Headphone output 6.35mm

Formats files for USB:

MP3: MPEG-1 Audio Layer 3 44.1 or 48 kHz - 320 kb/s or less WMA: 44.1 kHz - 192 kb/s or less

Included Accessories

1x Detachable IEC power socket

1x Wireless antenna

1x FM antenna indoor

1x Remote control RC-EX3.1

1x Batterie

1x Manual

SPECIFICATIONS

Amplifier section

2x25W into 8Ω and 2x35W into 4Ω
Total harmonic distorition
< 0,2% à 1W
Signal to noise ratio > 70 dBA
Bandwidth: 20 Hz - 20 KHz
Speaker Impedance Compatibility

Wireless

Range : 4-8 Ω

Range: about 10 m

Tuner FM RDS and AM with 40 presets

CD Player (MP3/WMA)

USB slot (MP3/WMA)
Type-A
Recognized formatting: FAT

Connectors

1x Headphone (Jack 6.35 mm)

1x USB slot (Type-A)

1x Auxiliary input stereo RCA

1x Digital input: Optical and Coaxial

1x Wireless antenna

1x Subwoofer output (RCA)

1x FM antenna indoor

1x AM antenna indoor

4x Speakers terminals screw

4x Speakers terminals screw compatible banana plugs

