

EX-302 Stereo integrated amplifier 2x40W

Highlights

- ✓ Digital input
- ✓ Phono input
- ✓ MP3 input
- ✓ Headphone output



EX-302 This BC Acoustique Integrated Amplifier has been designed with an « audiophile spirit » and with the idea to allow music lovers looking for real « music fidelity » to be satisfied. The EX302 can deliver an output power of 2x40W RMS on 8 Ohms speakers and, thanks to its massive 250VA transformer, 2x80W RMS on 4 Ohms. The EX302 is equipped with 6 audio inputs including one digital (Optical/Coaxial) that allows to connect a modern TV on its digital audio output. A jack 3,5mm input is also available on the front panel to allow the user to connect any kind of audio portable player. A headphone output (jack 6,35mm) is also available. The EX302 also offers a « Pre-Out » RCA that allows to make a bi-amping capability (with another power-amp).

HIGHLIGHTS

High quality manufacturing
 Massive toroidal transformer
 Large power output amplifier stage
 Ability to drive any kind of speakers (including 8, 4 and 3 Ohms)

Optical and coaxial digital inputs
 Phono input
 MP3 input for iPhone
 Headphone output

SPECIFICATIONS

Continuous output power:
 2x40W into 8 Ohms
 2x80W into 4 Ohms
 THD < 0,01%
 Signal to noise ratio > 100dB
 Frequency response: 15 Hz - 25 kHz (0,5dB)

4x RCA inputs CD, Tuner, Aux 1, & MM phono
 1x Digital input (Optical & Coaxial)
 1x Jack 3,5mm input (MP3 front)
 1x RCA Pre-Out
 1x Pair of insulated speaker output
 1x Jack 6.35 mm Headphone outputs
 IEC power plug
 Remote control

Dimensions (WxHxD): 430x70x320 mm
 Weight: 6.1 kg

EAN CODE

Black finish (B): 0661799078245

DEEE

4.4 = 0,84 € H.T.

